

# ALR-F800

## Industrial UHF Fixed Reader



- ARM9 677MHz processor
- EPC Gen 2; ISO 18000-6c
- 512 MBytes DDR3 RAM, 2 GBytes Flash
- Wi-Fi



DSA



SDT



RUBY Program

## BENEFITS

- Compact form-factor, standard VESA M4 mounting threads
- Autonomous on-board state machine
- 8 Output / 4 Input / 12 VDC out (w/ DC power) GPIO



## FEATURES

- Flexible connectivity (LAN, USB, Serial)
- Wi-Fi & Bluetooth Capable via USB adapter
- Proven Alien Reader Protocol Feature-set & Syntax
- Plenum Rated (EAHS) per UL 2043

Need	Feature	Benefit
<b>Straight forward installation &amp; operation</b>	<ul style="list-style-type: none"> <li>• Alien ESCAPE enhanced built-in configuration tool (via web interface)</li> <li>• Alien Reader Protocol or LLRP</li> <li>• Smart reader/autonomous mode</li> </ul>	<ul style="list-style-type: none"> <li>• Built in configuration tools</li> <li>• Easy to set up and deploy</li> <li>• No additional costly controllers</li> <li>• Less maintenance and overhead</li> </ul>
<b>PoE and 12 VDC power option without compromise of output power</b>	<ul style="list-style-type: none"> <li>• With PoE power, outputs 31.5dBm – significantly more than other readers</li> <li>• Dynamically switches between power sources when power fails (when 12VDC also connected)</li> </ul>	<ul style="list-style-type: none"> <li>• Uses standard PoE switch/power injector</li> <li>• Flexibility to choose power source</li> <li>• Simplified installation</li> </ul>
<b>Dynamically self adjusts to optimize readability in noisy &amp; multiple reader environments</b>	<ul style="list-style-type: none"> <li>• Dynamic “Smart-throttling” in adverse RF environments</li> <li>• Intelligent real-time Phase Cancellation</li> <li>• Maximizes the sensitivity and interference rejection in all environments</li> </ul>	<ul style="list-style-type: none"> <li>• Maintains optimal sensitivity even in very noisy RF environments</li> <li>• More likely than competitors to read tags in high interference environments (other readers and RF sources)</li> </ul>
<b>Field manageable &amp; virtual obsolescence-proof</b>	<ul style="list-style-type: none"> <li>• Ability to add new features as available via OS update or conventional firmware update (versus h/w replacement)</li> <li>• MicroSD &amp; USB slots for added memory or peripherals</li> </ul>	<ul style="list-style-type: none"> <li>• Field upgradeable/updatable</li> <li>• Ability to increase memory w/ microSD or USB</li> <li>• Ability to add external peripherals via USB</li> </ul>



Alien Technology Asia – Korea  
 #909, 99, Digital-ro 9-gill Gumcheon-gu Seoul, 08510 Korea  
 Tel: +82-70-7012-1317 Fax: +82-2-868-1710  
 www.aliensia.com support@aliensia.com

# ALR-F800

## Industrial UHF Fixed Reader

### Reader Practicality and Power

ALR-F800 provides the highest transmit power of any reader when operating Power-over Ethernet (PoE) power while simultaneously allowing seamless switching between DC power and PoE power.

This removes the need to determine power source in order to obtain optimal reader performance, but rather enables choice of the most cost effective source for your application.

Alien **GATESCAPE** built-in configuration tool simplifies reader set-up and configuration via an easy to navigate web interface.



- 1 Standard LAN (RJ45) & PoE
- 2 12VDC Power
- 3 Reset Button
- 4 USB Host (USB-A connector)
  - USB memory stick expansion
  - USB Wi-Fi or Bluetooth enablement
  - 5VDC / 500mA power source for peripherals
- 5 USB Console (USB-B connector)
  - Alternate serial communications port (backdoor)
- 6 microSD card slot for additional memory expansion
- 7 Serial Port (DB9 connector)
  - Serial connectivity for legacy and current serial based devices
- 8 GPIO Connector
  - 8 Output pins for light stacks, controllers, etc.
  - 4 Input pins for motion sensors, switches, etc.
  - 12VDC (when using 12VDC power) power pins

### Usable Performance

ALR-F800 utilizes **DSA** (Dynamic Self-Adapting), which monitors the RF environment in realtime and manipulates a number of parameters, filters and tuning metrics providing real-time “Smart Throttling” optimizing reader behavior to maximize the tags read.

### Industry Standard I/O and Firmware Personality

The reader is extensible via industry standard I/O including micro-SD cards (for adding memory) and USB (for accessing wireless I/O such as Wifi and cellular modems). Most readers are programmable but this reader also has the ability for the RF subsystem to be updated via firmware. These updates help protect the ALR-F800 from obsolescence.



# ALR-F800

## Industrial UHF Fixed Reader

### Reader Kits

Kit Name	Target User	Kit Model Number XXX = Country Code	Contents	Notes
Reader	Large installations that have an existing PoE power supply infrastructure.	ALR-F800-XXX-RDR-ONLY	Reader only (country/region specific) I/O mating connector	No power supply (DC or Power-over Ethernet Injector) provided. If you need one, order the "Kit" below.
Reader Kit	Someone planning to evaluate or develop with the reader and required a power source to power the reader. Good for working on a lab bench.	ALR-F800-XXX-RDR-KIT	ALR-F800 Reader (country/region specific) PoE Injector Power Cable for PoE injector/reader Two Ethernet cables USB Cable (Type B to A) I/O mating connector	Reader with a power supply in the form of a Power-over-Ethernet Injector (which supplies both power and data to the reader). Comes complete with power cord for the injector and 2 Ethernet cables, one for data and one for both data and power).
Reader Dev Kit	Someone planning to evaluate or develop with the reader and required a power source to power the reader. Good for working on a lab bench.  Provides an antenna, antenna cable, tags, and all miscellaneous cables, brackets in a carry case for one-stop-shop evaluation	ALR-F800-XXX-DEV-C	ALR-F800 Reader (country/region specific) PoE Injector Power Cable for PoE injector/reader Two Ethernet cables USB Cable (Type B to A) I/O mating connector DC Power Supply Unit Serial cable One ALR-8697 Antenna 20ft antenna cable Tag sample pack Micro-SD Card VESA Mounting Bracket Black carry case with foam inserts	Reader with a power supply in the form of a Power-over-Ethernet Injector (which supplies both power and data to the reader). Comes complete with power cord for the injector and 2 Ethernet cables, one for data and one for both data and power).  Provides everything possible for complete system evaluation without the need to purchase RFID antenna, coax cables etc.

Model Number	ALR-F800 (All Models and Country Variants)
Architecture	ARM9 677MHz processor, Linux, 512 MBytes DDR3 RAM, 2 GBytes Flash
Supported RFID Tag Protocols	EPC Gen 2; ISO 18000-6c
Reader Protocols	Alien Reader Protocol, LLRP
LAN Protocols	TCP/IP, NTP, DNS, DHCP, SNMP
Dense reader management	Dense Reader Mode, auto event triggering and event management
Power	Power over Ethernet or robust universal AC-DC power converter; 100-240 VAC, 50/60Hz
Reader Power (with PoE)	≥31.5 dBm (lower as required by law in specific regions - see tables below)
Communications	LAN TCP/IP (RJ-45), RS-232 (DB-9 F), USB Host, USB Console
Antennas	4 reverse polarity TNC monostatic ports; circular or linear polarization; near and far field compatible
General Purpose I/O	Optically isolated. 0-24VDC rail. 4 inputs. 8 outputs (1500mA capacity).
Dimensions	(L) 20.2 cm x (W) 19.1 cm x (D) 2.8 cm (7.5" x 7.9" x 1.1")
Weight	0.85 kg (1.88 lb)
Operational Temperature	-20°C to +50°C (-4°F to +122°F)
Environmental Rating	IP53 and Plenum rated UL-2043
LED Indicators	Power, CPU, Read, Sniff, Ant 0-3
Software SDK	Java, .NET, Ruby APIs
RoHS	EU 2002/95/EC compliant



Alien Technology Asia – Korea  
 #909, 99, Digital-ro 9-gill Gumcheon-gu Seoul, 08510 Korea  
 Tel: +82-70-7012-1317 Fax: +82-2-868-1710  
 www.aliensia.com support@aliensia.com

# ALR-F800

## Industrial UHF Fixed Reader

### Models by Country

Model Number	Countries	Frequency	Transmit Channels	Channel Spacing	RF Power	Compliance Certification
ALR-F800-RDR-KIT	USA, Bolivia, Canada, Colombia, Mexico, Panama, Puerto Rico, Venezuela	902 - 928 MHz	50	500 KHz	4W EIRP	Emissions: FCC Part 15 Safety: cTUVus tested to: CAN/CSA-C22.2 No.60950-1-03, and UL 60950-1:2007 specifications IEC 60950-1 and EN60950-1, UL 2043 ATT, CRC, IFETEL, ASEP, CONATEL
ALR-F800-ARG-RDR-KIT	Argentina*	902 - 928 MHz	50	500 KHz	4W EIRP	Enacom
ALR-F800-BRA-RDR-KIT	Brazil	902 - 907.5 MHz & 915 - 928 MHz	35	500 KHz	4W EIRP	Emissions: Agência Nacional de Telecomunicações - ANATEL Safety: UL Brazil
ALR-F800-CHN-RDR-KIT	China, Singapore	920 - 925 MHz	16	250 KHz	2W ERP	Emissions: CMII Safety: IEC 60950-1:2005 2nd edition & CCC
ALR-F800-EMA-RDR-KIT	Europe, UAE, New Zealand, South Africa	865.7 - 867.5 MHz	4	600 KHz	2W ERP	Emissions: ETSI EN 302-208-2 (4 channel plan), EN 301-489. Safety: EN 60950, EN 50364
ALR-F800-IND-RDR-KIT	India	865.6-867.0 MHz	3	600 KHz	2W ERP	Emissions: EN 302-208-2, EN 301-489. Safety: IS 13252 (Part 1)/IEC 60950-1
ALR-F800-ID-RDR-KIT	Indonesia	923 - 925 MHz	4	500 KHz	2W ERP	Ministry of Communications and Information Technology
ALR-F800-JP3-RDR-KIT	Japan*	915.8 - 921.4 MHz	4	1200KHz	4W EIRP	ARIB STD-T106
ALR-F800-KR2-RDR-KIT	South Korea*	916.7 - 920.9 MHz	6	600KHz	4W EIRP	KCC
ALR-F800-MY-RDR-KIT	Malaysia	919 - 923 MHz	8	500 KHz	2 W ERP	SIRIM
ALR-F800-RSA-RDR-KIT	South Africa	915.4 - 919 MHz	17	200KHz	4W EIRP	Emissions: ICASA Safety: NRCS
ALR-F800-TAI-RDR-KIT	Taiwan	922 - 928 MHz	19	250KHz	1W ERP	NCC
ALR-F800-URY-RDR-KIT	Uruguay, Peru	916 - 928 MHz	23	500 KHz	4W EIRP	Unidad Reguladora de Servicios de Comunicaciones (URSEC), Ministerio de Transportes y Comunicaciones
ALR-F800-VN1-RDR-KIT	Vietnam	918 - 923 MHz	9	500 KHz	500 mW ERP	QCVN 46:2016/BTTTT, QCVN 18:2014/BTTTT
ALR-F800-WR1-RDR-KIT	Australia, Hong Kong, Thailand, New Zealand	920 - 925 MHz	8	500 KHz	4W EIRP	ACMA, OFTA, RSM

\* Due to country specific regulations, power supplies must be obtained locally for Argentina, Japan and South Korea



Alien Technology Asia – Korea  
 #909, 99, Digital-ro 9-gill Gumcheon-gu Seoul, 08510 Korea  
 Tel: +82-70-7012-1317 Fax: +82-2-868-1710  
 www.aliensia.com support@aliensia.com